

▶ Thank you for choosing **SurgiTel®!**

Your SurgiTel® LED headlight has been designed to meet the demanding needs of today’s clinical professionals by allowing you to see, work, and feel your best.

▶ TECHNICAL DATA

LED Light	Several optics available
LED Life (Estimated on intensity used)	Up to 10,000 hours
Battery	Rechargeable Lithium Ion Battery, 7.4V 2,600 mAh
AC Charger	Input: 100-240V, 50-60Hz, 0.5A Output: +8.4V, 1.5A

▶ GENERAL WARNINGS

- The user of this product should be thoroughly familiar with the use and care of this product.
- The user should carefully study the manual before making any attempt to use this product clinically.
- Before each procedure carefully inspect the LED system to ensure proper maintenance.
- Use care not to point the light directly at the eyes during operation; patient use of safety glasses is recommended.

FIRE HAZARD: DO NOT PLACE THE LED LIGHT UNIT ON ANY FLAMMABLE OBJECT WHILE IT IS OPERATING.

WARNING:

- Improper assembly of LED cable plug and LED cable inlet on battery pack can lead to damage. Do not force fit and make sure orientation of joining parts is correct during assembly.
- The LED light unit will get hot when left on. Handle with care. It is recommended to turn off the LED before handling LED light or making any adjustments to it.
- Avoid direct light contact with the eyes.
- Avoid direct light irradiation in patient’s eyes; patient use of safety glasses is recommended.

Battery Charger & AC Power Adapter

- Use only the Battery Charger & AC Power Adapter supplied with this system
- Do not disassemble, modify or short circuit
- Do not leave in hot places, such as inside a car or outside in hot weather
- Do not allow to get wet



▶ WARRANTY

SurgiTel’s mission is to provide the best products for your *Vision & Ergonomics at Work*. To support this commitment SurgiTel® warranties all of its products.

SurgiTel® strives to make the best loupes and light systems available. Please inspect and try on product immediately upon receipt. If you notice any issues, contact our customer service department at 800-959-0153.

For both warranty and out-of-warranty issues, contact SurgiTel® Customer Service regarding repairs.

Warranties vary by product. Check www.surgitel.com/warranty for more details. Check www.surgitel.com/help for up to date care information/instructions. Please keep up to date on care information/instructions, as warranties can be affected if product is misused.

▶ PATENT

Touch-Free Active IR sold and manufactured pursuant to a licence from Designs for Vision, Inc., Patent No. US RE46,463E. The Eclipse LED light uses an active IR. Its sensing electronics were designed using a SurgiTel patented design concept (US 10,066,816 B2), and the beam-forming optics use patented optical technologies (US 9,383,077 B2; US 9,494,299 B2).

SurgiTel®
a division of General Scientific Corporation
77 Enterprise Drive • Ann Arbor, MI 48103-9503
E-mail info@surgitel.com • www.surgitel.com


Doc No. 26226B

SurgiTel®









Eclipse LED

USER INSTRUCTIONS



► CLASSIFICATION

- Protection against electric shock: Class II including AC/DC Adapter.
- Applied parts : No applied parts.
- Protection against harmful ingress of water: ordinary IPXO.

	Direct current		Class II equipment
	CE mark		Serial No.
	Alternating current		Attention, consult accompanying documents


► MAINTENANCE

Storing the LED system in a safe place will prolong the life of the unit. The following guidelines will help in sustaining the LED systems useful life:

- Keep the optical face on the light unit from touching hard surfaces which may cause scratches on the surface. Scratches on the surface will diminish the light quality.
- When cuts or punctures are visible on the system’s light cord, the wireless LED system is no longer safe to use; it should be taken out of service immediately.

Fixing Hinge Tension (too loose or too tight):

- Step 1: Use provided hex key to remove hinge set screw (see photo to the right)
- Step 2: Use two flat-head screwdrivers (placed on each side) to loosen/tighten special screw and nut
- Step 3: Once desired tension is met, reassemble and tighten set screw



► CLEANING



- Do not immerse in water or any liquid; wipe down with damp cloth. Do not use HOT or COLD water; using “room-temperature” water is acceptable
- Avoid using running water and disinfectant sprays on or near open slots located on light unit. Carefully wiping with damp cloth is ok.
- Do not use Lysol® or any disinfectants containing glutaraldehydes, iodophors, ammonia, alcohol, or ethanol
- Do not autoclave

Disinfection: Use SciCan® “OPTIM 33 TB” wipes/solution only.
*Note: SciCan® OPTIM 33 TB solution can be purchased through SurgiTel in 8 oz. bottles

FACTORY REFURBISHMENT CLEANING: is available if you come across a difficult cleaning situation. Call customer support for details: 800-959-0153

► OPERATION

- Charge Time (Battery Pack) = approximately 2-3 hours
- Maximum continuous operation at full load is approximately 7 hours
- Attach the LED light to loupes or glasses using an appropriate adapter
- Use the included garment clips to route the cable appropriately
- Power switch (1):
Rotate to turn light off/on
- Light intensity (1):
Adjust the position of the knob to adjust the light level
- Rechargeable inlet (2):
Recharges the battery with the aid of an AC charger
- Battery charge level indicator light (3):
GREEN = fully charged, RED = charging, FLASHING RED = error
- Battery pack battery power indicator light (4):
GREEN = 2-6 hours, RED = less than 2 hours, FLASHING RED = less than 1 hour
- Power switch (5):




Note: Battery pack must be powered on for this function to work.

STEP 1 - Turning on LED light

Allow 60 seconds of uninterrupted use for the on/off motion sensor to warm up and adjust to your room lighting conditions.

STEP 2 - Operating on/off motion sensor

- A. First, place your hand about 9 inches in front of the Eclipse LED sensor.
- B. Next, slowly move your hand towards the motion sensor to turn on/off your Eclipse LED.



Note about light-cured composites

- Although it is not recommended to use this LED Light while working with light-cured composites, setting the light to a lower light intensity may allow you to work briefly with materials before hardening
- Using the appropriate COLOR FILTER (orange filter) is STRONGLY RECOMMENDED when using light-cured materials with the LED Light


► OPERATING CONDITION

- Ambient temperature range 10 to 40°C
- Relative humidity range 30 to 75%
- Atmospheric pressure range 70 to 106 kPa

► TRANSPORT & STORAGE CONDITION


- Ambient temperature range -40 to 70°C
- Relative humidity range 10 to 100%
- Atmospheric pressure range 50 to 106 kPa

► ATTACHING LIGHT ADAPTER TO LOUPE



- Attach the LED light to loupes or glasses using appropriate adapter


► ADJUSTMENTS



- Attach light cord to frame by sliding both o-rings onto temple arm, as shown

Note: O-rings are attached to LED cord

► CABLE ROUTING



Warning:

Battery Control Pack Belt Clip

- Improper use of the belt clip can lead to product damage. Refer to photos shown to the right for correct use.



Battery Control Pack Placement

- Positioning the battery pack incorrectly can lead to belt clip damage. Refer to the photos shown to the right for correct placement.

